

2.Clam-Shell Socket(SOP,SOL,SSOP,TSOP)

Unit: mm

Part Number	Pin Count	Pitch	Body Width	Tip-Tip
FP-8(16H)-1.27-06	8	1.27	3.9	6.9
FP-8(20)-0.65-02A	8	0.65	4.4	6.4
FP-8(24)-0.65-01A	8	0.65	5.6	7.6
FP-14(16H)-1.27-05	14	1.27	3.9	6.9
FP-14(20)-1.27-06	14	1.27	5.3	7.8
FP-14(20H)-1.27-06	14	1.27	5.3	7.8
FP-14(28H)-1.27-07	14	1.27	7.9	10.4
FP-16-0.65-01A	16	0.65	4.4	6.4
FP-16-0.65-02A	16	0.65	4.4	6.4
FP-16-1.27-05	16	1.27	3.9	6.9
FP-16(20)-1.27-06	16	1.27	5.3	7.8
FP-16(28H)-1.27-07	16	1.27	7.9	10.4
FP-16(28H)-1.27-08	16	1.27	7.9	10.5
FP-18(20)-1.27-06	18	1.27	5.3	7.8
FP-18(28H)-1.27-07	18	1.27	7.9	10.4
FP-20-0.65-01A	20	0.65	4.4	6.4
FP-20-0.65-02A	20	0.65	4.4	6.4
FP-20-1.27-03	20	1.27	7.6	10.2
FP-20-1.27-06	20	1.27	5.3	7.8
FP-20(28H)-1.27-06	20	1.27	8.4	12
FP-20(28H)-1.27-07	20	1.27	7.9	10.5
FP-20(28H)-1.27-08	20	1.27	7.9	10.5
FP-24-0.65-01A	24	0.65	5.6	7.6
FP-24-0.65-02A	24	0.65	5.6	7.6
FP-24-1.27-04	24	1.27	8.4	12
FP-24-1.27-08	24	1.27	5.3	8
FP-24(28H)-1.27-07	24	1.27	7.9	10.4
FP-24(28H)-1.27-08	24	1.27	7.9	10.5
FP-28-0.8-01	28	0.8	7.2	9.3
FP-28-1.27-06	28	1.27	8.4	12
FP-28-1.27-06B	28	1.27	8.4	12
FP-28-1.27-07	28	1.27	7.9	10.4
FP-28-1.27-08	28	1.27	7.8	10.5
FP-28-1.27-08A	28	1.27	7.9	10.5
FP-28-1.27-09	28	1.27	8.6	11.8
FP-28-1.27-10	28	1.27	7.9	12
FP-28-1.27-15B	28	1.27	9	11.6
FP-28-1.27-17A	28	1.27	8.6	11.8
FP-28-1.27-22	28	1.27	8.6	11.8
FP-28(30)-0.65-01A	28	0.65	5.6	7.6
FP-30-0.65-01A	30	0.65	5.6	7.6
FP-32-1.0-02	32	1	5.4	7.8
FP-32-1.0-03	32	1	7.5	9.3
FP-32-1.27-10	32	1.27	11.6	14.2
FP-32-1.27-03	32	1.27	8.9	12.5
FP-32-1.27-06	32	1.27	10.7	14.2
FP-48-0.8-03	48	0.8	14X20	15.6